

Motio 30 -12V Programming

- Step 1** Push motor head once blind will jog
Press & Hold STOP button-----blinds jogs then Beeps
- Step 2** **Setting the Upper limit**
Go Up till you reach the desirable UPPER limit then→Press & hold UP+STOP together till the blind jog
- Step 3** **Setting the Lower limit**
Go DOWN till you reach the desirable LOWER limit then→Press DOWN +STOP together till the blind jogs

NOW THE BLIND IS READY FOR USE

Adjust Upper & Lower Limit

- _ Reach the limit you want to adjust UP or DOWN
- _ Press and Hold UP & STOP or DOWN & STOP together till the blind jogs
- _ Adjust the Limits by going to the desire new position
- _ Press and Hold UP & STOP or DOWN & STOP together till the blind jogs

Setting Favorite Position

Move Blinds to the favorite position then Press P2 then press stop 3 times till blind jogs

Speed Control

P2→Up for high speed P2→Down for slow speed

Reverse Motor Direction

Press Motor head and hold till it jogs 3 times

Factory reset

Press Motor head and hold it till it jogs 4 times